



MODELLO	DESCRIZIONE	PREZZO €
Preamplificatori a Valvole in Classe A		
 	<p>LS 100 tube single-ended preamp</p> <p>Preamplificatore a valvole in Classe A - Single-ended design. Valvole impiegate: 2x 6SN7 (Driver), 1x 5AR4/GZ34 rettificatrice; Zero global Negative feedback; Comando a distanza in dotazione con dieci funzioni di controllo; Gain: 12dB; Impedenza d'ingresso: 38 Kohm; Impedenza d'uscita: 300 ohm; Risposta in frequenza: 20 Hz-100 KHz ±1dB; Rapporto S/N: 125 dB; Ingressi stereo: 5 Linea RCA, 1 Linea XLR, *1 Modulo Phono MM / MC (valvole impiegate: 1x 12AX7, 1x 12AU7), 1 HT/BP (bypass home theater), 1 Tape Monitor; Uscite stereo: 2 RCA, 1 XLR, 1 Tape Out RCA. Finitura Black. Garanzia: 2 anni - Solo esposto. Dimensioni: 45x15x45 cm (LxHxP); Peso: 11 kg;</p> <p>*Modulo Phono: MC: Guadagno totale = 63 dB (incluso lo stadio preamp) MM: 12AX7 sostituita con 12AU7 = 48 dB di guadagno. Caricamento: 50, 100, 500, 1K, 47K, 100pf tramite dip switch interni. Utilizzare 1x 12AX7 (ECC83) e 1x 12AU7 (ECC82) per un guadagno maggiore o 2x 12AU7 per un guadagno inferiore, ad esempio, le 12AU7 amplificheranno abilmente una magnete mobile o una bobina mobile ad alta uscita.</p>	<p>3.499</p> <p>(5.499 con modulo phono MM/MC)</p> 
<p>Technical Specs</p> <p>Tube Complement: (2) 6SN7 driver tubes; (1) 5AR4 rectifier tube (may also use 5U4GB and 5V4GB). Internal tube rectified, solid state regulated power supply. Features: Four sets of RCA inputs. One set of XLR inputs (wired single-ended). Two sets RCA main outputs. One set of XLR main outputs (wired single-ended). One set of RCA Tape outputs. One set of RCA Monitor Inputs. One set of RCA Home Theater Bypass (HT/BP) inputs. Two 12V remote trigger outputs. Gain: 11 dB Input Impedance: 38Kohms. Output Impedance: 300 ohms. Frequency Response: 20hz-100Khz (+/-1dB). Max input signal level: 10 Vrms Max output signal level: 37 Vrms Headphone Amp Power: 1.5 Watts (32 ohm - 600 ohm load). Phono Option: MM/MC (Gain = 48dB/63dB). Tube Complement: (1)12AX7, (1)12AU7. Loading: 50, 100, 500, 1K, 47K, 100pf. Inputs: One pair RCA.</p>	 	